

## Test Report of Certification



**SpectraLink 8440 VoWiFi Handset**

with

**HiPath 3000**

**Test Status: released**  
**Release Date: January 23, 2012**

Siemens Enterprise Communications GmbH & Co. KG 2011

Issued by:  
Siemens Enterprise Communications GmbH & Co.KG  
Hofmannstraße 51  
D-81359 Munich

Siemens Enterprise Communications GmbH & Co. KG is a Trademark Licensee of Siemens AG

Copying of this document and giving it to others and the use or communication of the contents thereof, are forbidden without express authority. Offenders are liable to the payment of damages. All rights reserved in the event of the grant of a patent or the registration of a utility model or design.

## Contents:

<b>History of Change</b> .....	<b>3</b>
<b>1 Overview</b> .....	<b>4</b>
<b>1.1 Test Object</b> .....	<b>4</b>
1.1.1 Basic Equipment .....	4
1.1.2 Polycom VoWiFi.....	4
<b>1.2 Test Strategy</b> .....	<b>4</b>
1.2.1 Test Intensity .....	5
1.2.2 Measuring / Test Instruments .....	5
<b>1.3 Realisation Data</b> .....	<b>5</b>
<b>1.4 Test Results Summary</b> .....	<b>5</b>
1.4.1 Problems .....	5
1.4.2 Restrictions .....	5
1.4.3 Remarks .....	5
<b>2 Configuration</b> .....	<b>6</b>
<b>2.1 Polycom devices</b> .....	<b>6</b>
<b>2.2 HiPath 3000</b> .....	<b>6</b>
<b>2.3 HiPath Wireless Controller</b> .....	<b>6</b>
<b>2.4 Configuration Block Diagram</b> .....	<b>6</b>
<b>3 Test Results in Detail</b> .....	<b>7</b>
<b>3.1 Tests</b> .....	<b>7</b>
3.1.1 Connectivity and Basic Operation.....	7
3.1.2 Basic call .....	8
3.1.3 Telephony features .....	9
3.1.4 Audio features .....	13
<b>3.2 Remarks</b> .....	<b>14</b>
<b>4 Configuration Data</b> .....	<b>15</b>
<b>4.1 HiPath 3000</b> .....	<b>15</b>
4.1.1 System Basics.....	15
<b>4.2 Polycom VoWiFi</b> .....	<b>15</b>
4.2.1 Documentation .....	15
<b>4.3 Wireless network</b> .....	<b>15</b>
<b>5 Confirmation</b> .....	<b>16</b>

## History of Change

<u>Date</u>	<u>Description</u>	<u>Name</u>
September 2011	Initial Version	Eddy De Braekeleer SEN Service PS E-Mail: <a href="mailto:eddy.debraekeleer@siemens-enterprise.com">eddy.debraekeleer@siemens-enterprise.com</a> Phone: +32.2.406.7316
September 14 – 20 December 5-6, 2011	Certification tests	Karel Eeckelaert E-Mail: <a href="mailto:karel.eeckelaert@siemens-enterprise.com">karel.eeckelaert@siemens-enterprise.com</a> Phone: +32.2.406.7119
Januari 9, 2011	Review Partner	Oliver Wick Polycom E-Mail: <a href="mailto:oliver.wick@Polycom.com">oliver.wick@Polycom.com</a> Phone: +49 811 9994-266
Januari 23, 2011	Final review	Eddy De Braekeleer SEN Service PS E-Mail: <a href="mailto:eddy.debraekeleer@siemens-enterprise.com">eddy.debraekeleer@siemens-enterprise.com</a> Phone: +32.2.406.7316
Januari 23, 2011	Release	Eddy De Braekeleer SEN Service PS E-Mail: <a href="mailto:eddy.debraekeleer@siemens-enterprise.com">eddy.debraekeleer@siemens-enterprise.com</a> Phone: +32.2.406.7316

## 1 Overview

### 1.1 Test Object

#### 1.1.1 Basic Equipment

<b>Test system:</b>	HiPath 3000
<b>Software Version:</b>	H3K_V8_R5_7_0.107
<b>Wireless Controller</b>	C2400: 07.11.02.0004

#### 1.1.2 Polycom VoWiFi

<b>Certification:</b>	Test of interface functionality between the HiPath 3000 and the Polycom SpectraLink VoWiFi handset
<b>Test Equipment:</b>	HiPath 3000 and the Siemens HiPath Wireless C2400 Controller and Access Points (AP)
<b>Software Release:</b>	8440: V 4.0.0.20561
<b>HW / FW Release:</b>	
<b>Manufacturer:</b>	Polycom
<b>Description:</b>	The 8440 VoWiFi handset functions as a SIP device registered on the Openscape Voice Server.
<b>Documentation:</b>	- Configuration Manual: Polycom SpectraLink
<b>Test Network:</b>	Test network of HiPath Ready Lab Brussels
<b>Test Configuration:</b>	See section 2.3

### 1.2 Test Strategy

This certification test for the **Polycom** phones listed below with the **Siemens HiPath 3000 V8** focused on the verification of the SIP interface in the following scenarios:

- Basic phone configuration and registration
- Basic calls
- Telephony feature verification
- Audio features, including codecs and DTMF
- Basic WLAN test were performed

Other scenarios, including data security / encryption and mass provisioning (via DLS) was not part of the certification.

**Regarding the compliance with acoustic standards no tests were performed.**

### 1.2.1 Test Intensity

Scopes of the tests are to execute / to verify the solution performs within the limits of the system requirements, targeting the end product. To accomplish this, feature and solution based test cases are created, inspected, and executed under a real system environment (mirroring as close as possible real customer's environment).

**Note:**

The testing of the product with regard to compliance to requirements for Product Safety, EMV, Network Access Interfaces and Radiation Protection were not performed. Siemens Enterprise Communications therefore assumes no responsibility for the compliance to these requirements.

### 1.2.2 Measuring / Test Instruments

Tracing and monitoring available on all IP phones, servers, gateways and laptops. No special hardware required.

## 1.3 Realisation Data

**Test Preparation:** September 2011  
**Test Duration:** september 14<sup>th</sup> – 20<sup>th</sup>, December 5-6, 2011  
**Test Location:** Siemens Enterprise Communications  
Demeurslaan 134  
1654 Huizingen  
International Solution Lab  
**Test Personnel:** Siemens HiPath 3000,  
Karel Eeckelaert  
**Coordination:** De Braekeleer Eddy  
E-Mail: [eddy.debraekeleer@siemens-enterprise.com](mailto:eddy.debraekeleer@siemens-enterprise.com)  
+32 2 406 7316

## 1.4 Test Results Summary

For details please have a look at the test results.

### 1.4.1 Problems

### 1.4.2 Restrictions

### 1.4.3 Remarks

- 1) Certain tests failed due to the limited feature availability for SIP endpoints on the HiPath 3000. This is specified in the tests.

## 2 Configuration

### 2.1 Polycom devices

The Polycom devices have been configured according to the manual.


### 2.2 HiPath 3000

- HW Version: HiPath 3000 V8
- SW Version: H3K\_V8\_R5\_7\_0.107

### 2.3 HiPath Wireless Controller

- HW Version : C2400
- SW Version: V 7.41.05.003
- Access Points: AP3610

### 2.4 Configuration Block Diagram



**Ax** = +3223830-395/396 = Polycom SpectraLink handsets = DUT (device under test)

**Oy** = +3223830-390/391/393 = OptiPoint 500 / OpenStage IP phones

**Eu** = external PSTN phone u

**x, y, z, u** are digits from 0 to 9

### 3 Test Results in Detail

#### 3.1 Tests

The syntax of the abbreviations used in the test cases :

**Ax** = +3223830-395/396 = Polycom SpectraLink handsets = DUT (device under test)

**Oy** = +3223830-390/391/393 = OptiPoint 500 / OpenStage IP phones

**Eu** = external PSTN phone u

**x, y, z, u** are digits from 0 to 9

##### 3.1.1 Connectivity and Basic Operation

Test Case	Test Description	Result	Comment
1	Power up the handset and verify that the phone obtains a valid IP address from the <b>DHCP</b> server.	OK	
2	Connect a PC to the lab LAN and verify that access to the GUI of the test phone is possible.	OK	
3	Program the phone via GUI with the HiPath 3000 <b>registrar</b> information and verify that the phone registers	OK	
4	Change the OSV subscriber settings so that <b>Digest Authentication</b> is required for the registration. Verify that the phone does not register.	OK	
5	Add the information for <b>HTTP Digest Authentication</b> to the test phone settings and verify that the phone registers	OK	
6	Verify that the test phone displays the local date and time correctly that is provided by the lab's SNTP server (10.10.1.12).	OK	
7	The first node of the H3K is put out of service, which means that on the second node the backup registrar IP address is coming up.	NA	
8	The first node of the H3K is put in service again, which means that on the first node the registrar IP address is coming up.	NA	
9	The DUT is <b>registered</b> on the same number as the O1 phone. This can be used to use the two phones in parallel (like is done sometimes with a hardphone and a soft client).	NA	No forking possible on HiPath 3000

### 3.1.2 Basic call

For every test the HTTP Digest Authentication was enabled on the IP phones.

Test Case	Test Description	Result	Comment
10	Initiate a call from the DUT to <b>internal</b> subscriber A2. Verify that A2 is ringing (DUT receives ring back) and that the displays on the DUT and A2 show the correct called/calling number/name information.	OK*	Only number is shown, not name. This is a limitation of the HiPath 3000
11	From the previous test case answer the call at A2 and verify speech path between both phones. Verify that the phone displays show the correct information after the call connected.	OK	
12	From the previous test case <b>disconnect</b> the call at the DUT and verify that both phones return to idle state.	OK	
13	Repeat the previous call, but disconnect the DUT before A2 answers. Verify that the DUT returns to idle state.	OK	A2 shows missed call
14	Initiate a call from A2 to the DUT. Verify that the DUT is ringing (A2 receives ring back) and that the displays on the DUT and A2 show the correct called/calling number/name information.	OK*	Only number is shown, not name. This is a limitation of the HiPath 3000
15	From the previous test case answer the call at the DUT and verify speech path between both phones. Verify that the phone displays show the correct information after the call connected.	OK	
16	From the previous test case disconnect the call at the DUT and verify that both phones return to idle state.	OK	
17	Initiate a call from the DUT to <b>internal</b> subscriber O1. Verify that O1 is ringing (DUT receives ring back) and that the displays on the DUT and O1 show the correct called/calling number/name information.	OK*	Only number is shown on DUT, not name. This is a limitation of the HiPath 3000
18	From the previous test case answer the call at O1 and verify speech path between both phones. Verify that the phone displays show the correct information after the call connected.	OK	
19	From the previous test case <b>disconnect</b> the call at the DUT and verify that both phones return to idle state.	OK	
20	Repeat the previous call, but disconnect the DUT before O1 answers. Verify that the DUT returns to idle state.	OK	O1 shows missed call
21	Initiate a call from O1 to the DUT. Verify that the DUT is ringing (O1 receives ring back) and that the displays on the DUT and O1 show the correct called/calling number/name information.	OK*	Only number is shown on DUT, not name. This is a limitation of the HiPath 3000



22	From the previous test case answer the call at the DUT and verify speech path between both phones. Verify that the phone displays show the correct information after the call connected.	OK	
23	From the previous test case disconnect the call at the DUT and verify that both phones return to idle state.	OK	
24	Initiate a call from the DUT to an <b>external number</b> . Verify that the external phone is ringing (DUT receives ring back) and that the displays on the DUT and the external phone show the correct called/calling number.	OK	
25	From the previous test case answer the call at the external phone and verify speech path between both phones. Verify that the phone displays show the correct information after the call connected.	OK	
26	Initiate a call from an <b>external number</b> to the DUT. Verify that the DUT is ringing (external phone receives ring back) and that the displays on the DUT and the external phone show the correct called/calling number.	OK	
27	From the previous test case answer the call at the DUT and verify speech path between both phones. Verify that the phone displays show the correct information after the call connected.	OK	

### 3.1.3 Telephony features

Test Case	Test Description	Result	Comment
28	Initiate a call from the DUT to internal subscriber A2. Answer the call at A2. Put the DUT <b>on hold</b> and verify that it receives Music-on-hold.	OK	
29	From the previous test case retrieve the DUT from hold and verify speech path between the DUT and A2.	OK	
30	Initiate a call from internal subscriber A2 to the DUT. Answer the call at the DUT. From the DUT put A2 <b>on hold</b> and verify that it receives Music-on-hold.	OK	
31	Initiate a call from the DUT to internal subscriber A2. Answer the call at A2. Put the DUT <b>on hold</b> and verify that it receives Music-on-hold.	OK	
32	From the previous test case retrieve the DUT from hold and verify speech path between the DUT and A2.	OK	

33	Initiate a call from internal subscriber A2 to the DUT. Answer the call at the DUT. From the A2 put DUT <b>on hold</b> and verify that A2 receives Music-on-hold.	OK	
34	From the previous test case retrieve DUT from hold and verify speech path between the DUT and A2.	OK	
35	Initiate a call from the DUT to internal subscriber O1. Answer the call at O1. Put the DUT <b>on hold</b> and verify that it receives Music-on-hold.	OK	
36	From the previous test case retrieve the DUT from hold and verify speech path between the DUT and O1.	OK	
37	Initiate a call from internal subscriber O1 to the DUT. Answer the call at the DUT. From the DUT put O1 <b>on hold</b> and verify that it receives Music-on-hold.	OK	
38	From the previous test case retrieve the DUT from hold and verify speech path between the DUT and O1.	OK	
39	Initiate a call from internal subscriber O1 to the DUT. Answer the call at the DUT. From the DUT put O1 <b>on hold</b> and verify that it receives Music-on-hold.	OK	
40	From the previous test case retrieve the DUT from hold and verify speech path between the DUT and O1.	OK	
41	Initiate a call from the DUT to internal subscriber A2. Answer the call and initiate <b>consultation</b> at A2. Verify that the DUT receives Music-on-hold.	OK	
42	From the previous test case return from consultation and verify speech path between the DUT and A2.	OK	
43	Initiate a call from internal subscriber A2 to the DUT. Answer the call and initiate <b>consultation</b> at the DUT. Verify that A2 receives Music-on-hold while the DUT receives dial tone.	OK	
44	From the previous test case dial O1 at the DUT. Answer the call at O1. Verify that the DUT can <b>toggle</b> between A2 and O1.	OK	
45	From the previous test case initiate a <b>supervised transfer</b> at the DUT so that A2 and O1 are connected. Verify that A2 and O1 have speech path, the displays are correct, and that the DUT returns to idle state.	OK*	Displays are updated but DUT only shows number, not name (HiPath 3000 limitation)
46	Initiate a <b>supervised transfer</b> at the O1 so that the DUT and O2 are connected. Verify that the DUT and O2 have speech path, the displays are correct, and that the DUT returns to idle state.	OK*	Displays are updated but DUT only shows number, not name (HiPath 3000 limitation)

47	From the previous test case dial O1 at the DUT. Answer the call at O1. Verify that the DUT can <b>toggle</b> between O1 and O2.	OK	
48	From the previous test case initiate a <b>supervised transfer</b> at the DUT so that O1 and O2 are connected. Verify that O1 and O2 have speech path, the displays are correct, and that the DUT returns to idle state.	OK	
49	Initiate a call from the DUT to internal subscriber A1. Answer the call and initiate consultation at the DUT. Dial O1 and perform a <b>blind transfer</b> from A1 to O1. Answer O1 and verify that A1 and O1 have speech path, the displays are correct, and that the DUT returns to idle state.	NOK	HiPath 3000 does not support blind transfer.
50	Initiate a call from the O1 to the DUT. Answer the call on the DUT. Perform a <b>blind transfer</b> from the DUT to O2. Answer O2 and verify that O1 and O2 have a speech path, the displays are correct, and that the DUT returns to idle state.	NOK	HiPath 3000 does not support blind transfer.
51	Initiate a call from the DUT to the O2. Answer the call on O2. Perform a <b>blind transfer</b> from O2 to O3. Answer on O3 and verify that O3 and the DUT have a speech path, the displays are correct, and that the O2 returns to idle state	NOK	HiPath 3000 does not support blind transfer.
52	Initiate a call from the internal subscriber O1 to the O2. Answer the call on O2. Perform a <b>blind transfer</b> from O2 to the DUT. Answer on the DUT and verify that O1 and the DUT have a speech path, the displays are correct, and that the O2 returns to idle state	NOK	HiPath 3000 does not support blind transfer.
53	From the previous test case invoke the <b>last number redial</b> function on the DUT and verify that it calls O1.	OK	
54	Initiate a call to the DUT from an <b>external</b> number. Answer the call, then disconnect. Verify that the external number can be called from the call history list.	OK	
55	Initiate a call from the DUT to the internal subscriber O1. Answer the call and initiate a <b>three-way conference</b> from the DUT (conference master) with A1. Verify that all parties have speech path and that the displays on the phones indicate the conference.	OK	Only master shows conference, other parties show call to master
56	From the previous test case <b>release the conference master</b> (= DUT). Verify that the O1 and A1 are in two-party talk and the displays are updated accordingly.	NOK	Calls are terminated.
57	Initiate a call from the O1 to the internal subscriber DUT. Answer the call and initiate a <b>three-way conference</b> from the O1 (conference master) with A1. Verify that all parties have speech path and that the displays on the phones indicate the conference.	OK	Only master shows conference, other parties show call to master

58	From the previous test case <b>release the conference master</b> (= O1). Verify that the DUT and A1 are in two-party talk and the displays are updated accordingly.	OK*	Displays are not updated.
59	Call the O1 from the DUT after the <b>Do-Not-Disturb</b> function was activated on O1. Verify that the call is rejected (phone based DND).	OK	No visual feedback on DUT, only auditory.
60	Call the DUT from O1 after the <b>Do-Not-Disturb</b> function was activated via a service code. Verify that the call is rejected (system based DND).	OK*	System based DND not available for SIP-clients. Device based DND was successfully tested.
61	Activate <b>call forwarding (CFU)</b> on the H3K to A1. Call the DUT from O1 and verify that the call is forwarded to A1 (system based forwarding).	OK	
62	Activate <b>call forwarding (CFNR)</b> on the H3K to A1. Call the DUT from O1 and verify that the call is forwarded to A1 (system based forwarding).	OK	
63	Activate <b>call forwarding (CFB)</b> on the H3K to A1. Call the DUT from O1 and verify that the call is forwarded to A1 (system based forwarding).	OK	
64	Activate <b>call forwarding (CFU)</b> on the DUT to A1. Call the DUT from O1 and verify that the call is forwarded to A1 (device based forwarding).	NOK	Device-based forwarding is not supported for SIP-devices on H3K
65	Activate <b>call forwarding (CFNR)</b> on the DUT to A1. Call the DUT from O1 and verify that the call is forwarded to A1 (device based forwarding).	NOK	Device-based forwarding is not supported for SIP-devices on H3K
66	Activate <b>call forwarding (CFB)</b> on the DUT to A1. Call the DUT from O1 and verify that the call is forwarded to A1 (device based forwarding).	NOK	Device-based forwarding is not supported for SIP-devices on H3K
67	Put the DUT and O1 in the same pickup group. Call O1 from A2. While O1 is ringing, dial the <b>Group Pick-up</b> code (*57) from the DUT and verify that speech path to A2 is established and the display shows correct caller information.	NOK	Pick-up is not supported for SIP-devices on H3K
68	Call the DUT from O1. While connected, call the DUT from A1 and verify that a <b>call waiting</b> indication is presented on the DUT that shows the calling party information.	OK	
69	From the previous test case accept the waiting call and verify that speech path is established between the DUT and A1. Verify that O1 is put on hold.	OK	
70	O1 has <b>call waiting</b> disabled. O1 is on the call with O2 and the DUT tries to call O1.	OK	User hears busy tone on the DUT.
71	Call O1 from the DUT and <b>reject</b> the call at O1. Verify that the DUT indicates the call rejection.	OK	User hears short bust tone and call ends.
72	Call O1 from the DUT and <b>deflect</b> the call to O2. Verify that the DUT indicates the call deflection.	NA	H3K does not support call deflection.

73	Make the DUT busy and then call it from A2. Verify that the call is forwarded to the voicemail system (Xpressions Compact) and that the <b>message waiting indication (MWI)</b> on the DUT is turned on.	OK	
74	From the previous test case retrieve the voicemail message and verify that the MWI is turned off.	OK	
75	While the MWI is lit on the DUT, disconnect the DUT from power and force a reboot. Verify that after the reboot is complete, the MWI is turned on.	OK	
76	While the MWI is lit on the DUT, reboot the Xpressions Compact. Verify that after the reboot is complete, the MWI is turned on.	OK	
77	The O1 subscriber does call the DUT. The DUT does not answer and the O1 comes into the voice mailbox of the DUT. The O1 subscriber leaves a voice message. The DUT receives a MWI. The DUT calls the call-back number of XPR and reads its message. After reading and deleting its message the MWI is turned off.	OK	
78	The DUT is put in an <b>MLHG</b> (multi-line hunt group) together with O1, and A2.	NOK	SIP-endpoints in MLHG is not supported on H3K
79	Large conference call between O1, O2, O3, A1, A2 and A2 (up to 5 parties involved). The conference initiator is O1.	OK	

### 3.1.4 Audio features

Test Case	Test Description	Result	Comment
80	Configure A2 to use the G.729A codec only. Call the DUT from A2 and verify that the connection is established with G.729A (use Wireshark).	OK	
81	Configure the DUT for DTMF transmission via RFC 2833. Verify that from and to the DUT DMTF "telephony events" are sent.	OK	
82	Configure the DUT for DTMF transmission via RFC 2833. Verify that the Xpressions voicemail system can be accessed via DTMF.	OK	
83	Configure the DUT for DTMF transmission via RFC 2833. Verify that the DTMF tones are sent to and received from the PSTN.	OK	Remark: gateway supports RFC 2833

### 3.2 Remarks

#### Meanings of Abbreviations:

OK	Test case successful
NOK	Test case NOT successful
NA	Test case not applicable
NP	Test case not processed
NS	Situation not supplied
N *X	Error / restriction with description
* X	Remark to Functionality
DUT	Device Under Test
CFU	Call Forwarding Unconditional
CFNR	Call Forwarding on No Reply
CFB	Call Forwarding on Busy
MLHG	Multi Line Hunt Group
MoH	music-on-hold
DND	Do Not Disturb
AP	Access Points

Concrete deployment scenario of end customer requires additional technical verification!  
Please contact [hipath.ready@siemens-enterprise.com](mailto:hipath.ready@siemens-enterprise.com)

## **4 Configuration Data**

### **4.1 HiPath 3000**

#### **4.1.1 System Basics**

The Polycom SpectraLink devices were configured as regular SIP-users.

### **4.2 Polycom VoWiFi**

#### **4.2.1 Documentation**

Polycom Documentation is downloadable from the Polycom Support website.

### **4.3 Wireless network**

Wireless network settings (Siemens and Polycom):  
See Attachment WLAN\_Config\_C2400.pdf

Concrete deployment scenario of end customer requires additional technical verification!  
Please contact [hipath.ready@siemens-enterprise.com](mailto:hipath.ready@siemens-enterprise.com)

## 5 Confirmation

Testing personnel confirms that all the test cases were performed and that the results were as described in this document.

Oliver Wick  
Polycom

Karel Eeckelaert  
SEN Belgium

Concrete deployment scenario of end customer requires additional technical verification!  
Please contact [hipath.ready@siemens-enterprise.com](mailto:hipath.ready@siemens-enterprise.com)