

### Spectralink DECT Messaging Application Reference Guide

	voice	Int/Ext. Ringing	Application Protocol	MSF Support	Interface	Broadcast (Max length 19)	Internal messaging	Alarm Key	Text calls	fire & forget message	MWI	Menu select setup	ASCII string input	Charger in/out	LED control	Multi colour LED Ctrl	Colour Icons	Task lists & states	Task list ID	Rip-Cord	Running Dectector	No-movement	Man down	BGR-139 [Heartbeat]	Call control
							MSF I + II				MSF II				MSF III										
Third part controlled application						Both	Both																		
GAP Handset	X	X	-	-		-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-
Butterfly handset	X	X	X	X		X	X	-	X	X	X	X	X	X	-	-	-	-	-	-	-	-	-	-	X
Spectralink 7502 1)	X	X	X	X		X	-	-	-	X	X	-	-	X	-	-	-	-	-	-	-	-	-	-	X
Spectralink 7202	X	X	X	X		X	X	X	X	X	X	X	X	X	X	-	-	-	-	-	-	-	-	-	X
Spectralink 7212	X	X	X	X		X	X	X	X	X	X	X	X	X	X	-	-	-	-	-	-	-	-	-	X
Spectralink 7522	X	X	X	X		X	X	-	X	X	X	X	X	X	-	-	-	-	-	-	-	-	-	-	X
Spectralink 7532	X	X	X	X		X	X	-	X	X	X	X	X	X	-	-	-	-	-	-	-	-	-	-	X
Spectralink 7622	X	X	X	X		X	X	X	X	X	X	X	X	X	X	X	X	X	X	X	-	-	-	-	X
Spectralink 7642	X	X	X	X		X	X	X	X	X	X	X	X	X	X	X	X	X	X	X	X	X	X	X	X
Spectralink 7722	X	X	X	X		X	X	X	X	X	X	X	X	X	X	X	X	X	X	X	-	-	-	-	X
Spectralink 7742	X	X	X	X		X	X	X	X	X	X	X	X	X	X	X	X	X	X	X	X	X	X	X	X
ATEX handset (Funktel)	X	X				-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-
KIRK Wireless Server 1500	X	X	EMD	MSF I + II	RS232	X	X	X	X	X	-	X	X	X	X	-	-	-	-	-	-	-	-	-	-
IP-DECT Server 200	X	X	XML-RPC	MSF I + II + III	IP	X	X	X	X	X	X	X	X	X	X	X	X	X	X	X	X	X	X	-	-
IP-DECT Server 400	X	X	XML-RPC	MSF I + II + III	IP	X	X	X	X	X	X	X	X	X	X	X	X	X	X	X	X	X	X	-	-
IP-DECT Server 6500	X	X	XML-RPC	MSF I + II + III	IP	X	X	X	X	X	X	X	X	X	X	X	X	X	X	X	X	X	X	-	-
DECT Server 2500	X	X	EMD, XML-RPC	MSF I + II + III	IP + RS232	X	X	X	X	X	X	X	X	X	X	X	X	X	X	X	X	X	X	X	X
DECT server 8000	X	X	EMD, XML-RPC	MSF I + II + III	IP + RS232	X	X	X	X	X	X	X	X	X	X	X	X	X	X	X	X	X	X	X	X

Both: Can be used via Server GUI and via third party application.

Text Calls: Two way messaging can be setup by both and terminatd by both. Display text & call back numbers to handset, and key strokes from handset.

Fire & forget message: Message is sent or received by handset and a technical confirmation is returned.

Incoming [from handset point of view] MSF III can be send as fire & forget or as broadcast.

1): 7502 does only support a reduced version of MSF I. [outgoing MSF is disabled & Max text length is 24 characters, and Call Back Number is disabled]